



**Model Number**

**RTS 4P DB9**  
Ethernet DeviceServer


**Features**

- Two Ethernet connectors with built in hub
- Converts an RS 232, RS422, or RS485 device to Ethernet TCP/IP
- Metal housing
- Web-based configuration
- Modbus/TCP protocol integrated
- Port Mirroring


**Accessories**

- V45-G-10M-V45-G**  
Network cable
- V45-G**  
Non pre-wired cable connector

**Dimensions**



**Electrical connection**



**Technical data**

**General specifications**

Description	Connects up to 4 serial devices to ethernet Includes special firmware to run IDENT I System P read heads, IPT... Special firmware supports Modbus/TCP
Number of read/write heads	

**Indicators/operating means**

LED Tx	Green: Data being transmitted
LED PWR	LED solid: Has power and has completed boot cycle LED blinking: booting up
LED Link/Act	Red: Working ethernet connection
LED 100 MBit	Red: transfer rate 100 MBit/s Off: transfer rate 10 MBit/s

**Electrical specifications**

Rated operational voltage	$U_e$	5 ... 30 V DC , 110 / 220 Power Supply included with delivery
Current consumption		200 mA
Power consumption	$P_0$	4.8 W

**Interface**

Connection of	Ethernet
Physical	2 x RJ-45: Ethernet RJ-45 Connector
Protocol	SMTP HTTP TCP/IP MODBUS/TCP
Transfer rate	10 MBit/s or 100 MBit/s

**Interface 2**

Interface type	RS 232, RS 485, RS 422
Physical	4 x 9-pin Sub-D connector
Protocol	ASCII
Transfer rate	300 Bit/s ... 230.4 kBit/s

**Ambient conditions**

Ambient temperature	-37 ... 74 °C (-34.6 ... 165.2 °F)
Storage temperature	-40 ... 85 °C (-40 ... 185 °F)
Climatic conditions	air humidity max. 5 ... 95 %

**Mechanical specifications**

Protection degree	IP20
Material	
Housing	Metal sheet (steel), black-coated

Release date: 2010-04-26 22:51 Date of issue: 2010-04-26 905028\_ENG.xml

Subject to modifications without notice

Pepperl+Fuchs Group  
www.pepperl-fuchs.com

USA: +1 330 486 0001  
fa-info@us.pepperl-fuchs.com

Germany: +49 621 776-4411  
fa-info@pepperl-fuchs.com

Copyright Pepperl+Fuchs  
Singapore: +65 6779 9091  
fa-info@sg.pepperl-fuchs.com





Installation	panel mounting
Mass	approx. 3211 g

Release date: 2010-04-26 22:51 Date of issue: 2010-04-26 905028\_ENG.xml